


Stepper Motor Specifications:

MODEL	Phase	Step Angle	Connection Style	Current /Phase	Resistance /Phase	Inductance /Phase	Holding Torque	Rotor Inertia
		Deg/Step						
86STH65-2808B	4	1.8	parallel	4	0.65	3.9	3.5	1000
			series	2	2.6	15.6		
			unipolar	2.8	1.3	3.9	2.2	

Wiring Diagram



					DONGZHENG MOTOR		
					86STH65-2808B		
					STEPPER MOTOR		
REV.	QTY.	No.	SIG.	DATE	CLS. MAK	QTY	SCALE
DESIGN	Zhu Guanghua	2013.09.09	STD.		S		1:1
CHECK					PAGE OF		
PROC.			APPR.		ODZ. 243. 001		
							REV